



**Current transformer HF7A, 2500A/5A, Class 0.2S**

**Part no. HF7A-2500/5A-CLASS-0.2S**  
**Catalog No. 741H0068**

Similar to illustration

**Technical data ETIM 7.0**

|  |    |                  |                                |
|--|----|------------------|--------------------------------|
| Low-voltage industrial components (EG000017) / Current transformer (EC002048)  |    |                  |                                |
| Electric engineering, automation, process control engineering / Signal processing / Transformer / Current transformer (ecl@ss10.0.1-27-21-09-02 [AAB626014]) |    |                  |                                |
| Model  |    |                  | Through-feed current converter |
| Primary rated current  | A  | 2500             |                                |
| Secondary rated current  | A  | 5                |                                |
| Secondary rated apparent power   | VA | 10               |                                |
| Accuracy class   |    | 0.2              |                                |
| Over current limiting factor   |    | FS 5             |                                |
| Calibrated   |    | No               |                                |
| With shock protection  |    | No               |                                |
| Height opening   | mm | 60               |                                |
| Width opening  | mm | 80               |                                |
| Opening diameter   | mm | 65               |                                |
| Snap mounting  |    | Yes              |                                |
| With copper rail   |    | No               |                                |
| Secondary connection   |    | Screw connection |                                |
| Number of primary inputs   |    | 1                |                                |