

Current transformer HF6, 3000A/1A



Part no. **HF6-3000/1A**
741F0039

General specifications		
Product name		Eaton Distribution parts
Part no.		HF6-3000/1A
EAN		5703498701910
Product Length/Depth		149 millimetre
Product height		52 millimetre
Product width		158 millimetre
Product weight		2.335 kilogram
Compliances		RoHS conform
Product Tradename		None
Product Type		Distribution parts
Product Sub Type		None
Public Consumption		Yes
Product Family Description		ES-PMCC-PDC-Eaton Distribution parts
Globally Marketable		Yes
Product Specification Details		
Accuracy class (ratio)		3
Model		Through-feed current converter
Nominal current		3000 A
Number of inputs (primary)		1
Opening diameter		55 mm
Opening height - max		56 mm
Opening height - min		56 mm
Opening width - max		110 mm
Opening width - min		110 mm
Over current limiting factor		FS 5
Secondary connection		Screw connection
Secondary current input		1 A
Secondary rated apparent power		30 V-A

Technical data ETIM 9.0

Low-voltage industrial components (EG000017) / Current transformer (EC002048)		
Electric engineering, automation, process control engineering / Signal processing / Transformer / Current transformer (ecl@ss13-27-21-09-02 [AAB626019])		
Model		Through-feed current converter
Rated primary current	A	3000
Rated secondary current	A	1
Rated secondary apparent power	VA	30
Power consumption	W	
Accuracy class		3
Overcurrent limiting factor		FS 5
Calibrated		No
With shock protection		No
Height opening	mm	56 - 56
Width opening	mm	110 - 110
Opening diameter	mm	55
Snap mounting		Yes
With copper rail		No
Secondary connection		Screw connection

